

DIMMER COMPATABILITY LIST

Wave Lighting's LEDs were tested for compatibility with the below listed dimmers. The below compatibility chart can be used for guidance when selecting a dimmer and LED LAMP combination. Dimmers that do not appear on the chart may be compatible but have not been tested. Criteria includes level of dimmability and amount dimmer limits LED efficacy at dimmer's 100% setting. Contact sales with questions.

All testing has been performed with a stable main supply. The quality of the existing installation and wiring may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on site prior to installing LED LAMPs.

Best	~
Better	✓
Good	✓
Non-Compatible	×

	80CRI				LOW FLICKER - 90CRI				A19/E26
Dimmer Manufacturer/Model #	LR12	LR15	LR22	LR32	LT12	LT15	LT22	LT32	LE26
LUTRON SELV-303P-WH	V	✓	V	✓	V	V	V	V	×
LUTRON S-600H-WH	V	V	V	~	×	×	×	×	×
LUTRON LG-603PH-AL	V	V	V	V	×	×	×	×	×
LEVITON IPL06-10Z	>	>	>	>	>	>	>	×	V
LUTRON NTLV-600	>	>	>	>	>	>	>	>	×
LEVITON 6631-LW	V	V	V	V	>	V	V	V	×
LUTRON CTC2-153P	V	V	×	×	~	>	>	×	×
LUTRON DVCL-153P	>	>	>	×	>	×	>	×	V
LUTRON TTC9-153P	×	×	×	×	>	>	>	×	×
LUTRON DIVA DVCL-153P	V	V	V	V	>	>	>	×	V
LUTRON MA-600-WH	>	>	>	>	×	×	×	×	×
LEVITON DECORA 6672	V	V	V	V	V	✓	✓	✓	~
LEVITON 6674	V	V	V	V	>	>	×	×	V
LUTRON DV6200P-WH	V	V	V	~	×	×	×	×	×
LUTRON SKYLARK S-600P	V	V	V	~	×	×	×	×	×
LUTRON SKYLARK SELV-300P	V	V	V	~	V	V	V	V	×