


ACORN POST TOP FIXTURE 9017 **OUTDOOR DECORATIVE**



Wave Lighting's Acorn Post Top Fixture is ideal for any outdoor patio or walkway. This fixture is available in incandescent with A19 LED lamp option and is easily relamped via 2 screws in fitter. Wave Lighting's Acorns fit on a 3" diameter pole (sold separately) mounting hardware is included.

LED SOURCE OPTIONS

LIGHTWAVE LED - LR/LT

- 120V, 50/60 Hz
- AC Driver-On-Board Array
- Estimated 50,000 Hrs L₇₀
- Low Flicker (LT models)
- Surge Supression
- Dimmable (see compatible dimmer list)
- High Efficacy LED Light Source
- 3000K or 4000K CCT 80 or 90 CRI
- 5 Year Warranty

E26 MEDIUM BASE - LE26

- 120V, 50/60Hz
- "Screw-In" Medium Base A19/E26 LED Lamp
- Estimated 15,000 Hrs L₇₀
- Low Flicker (3K models)
- Dimmable (see compatible dimmer list)
- 3000K CCT 90CRI or 4000K CCT 80CRI
- 3 Year Warranty

E39 RETRO-FIT LED - LC

- 120-277V, 50/60Hz
- 250W Metal Halide Equivalent Lamp
- E39 Mogul Base Socket
- Estimated 50,000 Hrs L₇₀
- Surge Supression
- Available in 4000K CCT 80CRI
- Type 3, Type 5, or Dark Sky Distribution
- 5 Year Warranty



SPECIFICATIONS

- Cast Aluminum or Polycarbonate Fitters
- Black, White, or Bronze (Aluminum Only)
- Post Mount Only
- Polyethylene Acorn Diffuser
- Opal Textured Diffuser Options
- UL Listed For Wet Locations
- Non-Corrosive

GUIDE CODE: 9017-LR12C-BP

CALL FOR PHOTOMETRIC INFORMATION

ITEM #	LENS	LIGHT SOURCE	CCT	FITTER MATERIAL	OPTIONS
9017-Acorn	POLYETHYLENE Opal Textured	E26 MEDIUM BASE	C-4K W-3K	CAST ALUMINUM Black WH-White BZ-Bronze	MG-E39 Mogul Socket
		(1) 75W MAX Medium Base LE26-9.5W 800lm (E26 LED Lamp) †			
		120V LIGHTWAVE LED			
		LR12-13W 1000lm 80CRI LR15-15W 1400lm 80CRI LR22-23W 1900lm 80CRI LT12-12W 1040lm 90CRI LT15-16W 1400lm 90CRI LT22-24W 2020lm 90CRI			
		E39 RETRO-FIT LED 120-277V			
		LC5-24W 3120lm, Type 5 † LC3-20W 3000lm, Type 3 † LCD-24W 2400lm, Dark Sky †	C-4K		

† Lamp included.